

CYCLOPS

LIGHTING

CPX 2180P

DMX CHART

1 Ch

Channel	Function	Value	Description
1	Color Temp	0 --> 255	Adjust Color Temp (Cool and Warm White)

2 Ch

Channel	Function	Value	Description
1	Dimmer	0 --> 255	0% to 100% Dimmer
2	Color Temp	0 --> 255	Adjust Color Temp (Cool and Warm White)

3 Ch

Channel	Function	Value	Description
1	Dimmer	0 --> 255	0% to 100% Dimmer
2	Cool White	0 --> 255	0% to 100% Cool White LEDs 0%
3	Warm White	0 --> 255	to 100% Warm White LEDs

4 Ch

Channel	Function	Value	Description
1	Dimmer	0 --> 255	0% to 100% Dimmer
2	Cool White	0 --> 255	0% to 100% Cool White LEDs 0%
3	Warm White	0 --> 255	to 100% Warm White LEDs 0 Hz
4	Strobe	0 --> 255	to 20Hz Strobe

7 Ch

Channel	Function	Value	Description
1	Dimmer	0 --> 255	0% to 100% Dimmer
2	Cool White	0 --> 255	0% to 100% Cool White LEDs 0%
3	Warm White	0 --> 255	to 100% Warm White LEDs 0 Hz to
4	Strobe	0 --> 255	20Hz Strobe
5	Auto Program	0 --> 31	Safe
		32 --> 63	Color Temp Up Dimmer
		64 --> 95	Color Temp Down Dimmer Color
		96 --> 127	Temp Up/Down Dimmer
		128 --> 159	Color Temp Fade
		160 --> 191	Loop Change
		192 --> 255	Up/Down Loop
6	Speed	0 --> 255	0% to 100% Speed ID
7	ID	0 --> 255	Address Set