CYCLOPS LIGHTING

XL 54UV

DMX CHART

2 Channel Mode (A001 Mode)

Channel	Function	Description
CH1	W Dimming	Monotone light, from dark to light
CH2	Total Strobe	Total strobe, from slow to fast

1Channel Mode(d001 Mode)

Channel	Function	Description
CH1	W Dimming	Monotone light, from dark to light

Digital tube display menu Description

No.	content	Value range	Function and Description
1	A001	001- 512	DMX512Address setting-2CH
2	d001	001- 512	DMX512Address setting-1CH
3	u255	000 - 255	Monotone light, from dark to light
4	FH99	01 - 99	Strobe speed from slow to fast.