



# MD400-360RCD

## 400A Main Distribution Boxes

| INPUT                                       |                       |
|---|-----------------------|
| <b>Plugs</b>                                | <b>Breakers</b>       |
| 1 x Power Lock Set 500A Single Pole 3 Phase | 1 x 400A Main MCCB 4P |

| OUTPUT                                 |   |
|--|---|
| <b>Sockets</b>                         | <b>Breakers</b>                               |
| 6 x 16A CEE 240V 3 Pin Flanged Socket  | 1 x 40A RCD 4P<br>6 x 16A MCB 1P              |
| 2 x 16A CEE 400V 5 Pin Flanged Socket  | 2 x 40A RCD 4P<br>2 x 16A MCB 4P              |
| 4 x 32A CEE 400V 5 Pin Flanged Socket  | 4 x 40A RCD 4P<br>4 x 32A MCB 4P              |
| 2 x 63A CEE 400V 5 Pin Flanged Socket  | 2 x 63A RCD 4P<br>2 x 63A MCB 4P              |
| 4 x 125A CEE 400V 5 Pin Flanged Socket | 4 x Variable Earth Leakage<br>4 x 125A MCB 4P |

| CASE   |
|--|
| 24U Flight Case<br>Integrated Handles and Wheels |

| FEATURES   |
|--|
| <b>Digital Multimeter:</b> 1 x Digital Multimeter measures Amps, Volts & Frequency<br><b>Pilot Lights:</b> 3 x Red, 1 x Blue, 1 x Green<br><b>Protection Level:</b> RCD<br><b>Additional Information:</b> Made of Premium Components |