



FLASH 401RGB is a RGB audience blinder and strobe with 4x100 watts RGB COB LED sources. Every 2 LEDs are in an independant housing that can be rotated and directed easily. Each of the 4 LEDs is controlled separately adding a dynamic chase pixel mapping effect alongside the blinder and electronic strobe effect. It delivers a powerful output making it ideal for any size indoor stage, clubs and entertainment lighting installation.

SOURCE Light source: 4 x 100 watts RGB LED
LED life expectancy: 50,000 Hrs.

OPTICAL SYSTEM Beam angle: 60°
Each 2 COB LEDs in rotatable independant housing

DYNAMIC EFFECTS Dimmer: Linear adjustment
Electronic strobe: 0~20 Hz
4 zones control

CONTROL & PROGRAMMING Control protocols: DMX, Master-Slave, Auto Run
Control channels: 3, 7, 16 CHs

ELECTRICAL Input voltage: AC100~240V/50~60Hz
Power consumption: 360 watts

CONNECTIONS DMX connections: 3 pin XLR In/Out male and female
Power connections: PowerCon In/Out

PHYSICAL Dimensions: 370 x 370 x 180 mm
Net weight: 8.2 Kg
Color: Black
Housing: Aluminum
IP rating: 20